

THE FIGHTERS P-5000 & HI-P4000

FEATURES

- # CB & 10 m Mobile antennas
- # 17/7 PH Tapered whip
- # Very high Power Handling
- # P-5000: Low Loss Coil Made of 10 AWG / 2.5mm copper wire
- # Shaft version: 200mm / 8" Stainless Steel Shaft
- # Chrome plated brass parts CNC machined
- # Fully designed & Manufactured in Italy

TECHNICAL DATA

Impedance:	50 Ω
Frequency range:	27 ... 30 MHz
Polarization:	linear vertical
SWR @ res. freq.:	≤ 1.2
Max. power:	
P-5000	1500 Watts (CW) continuous
	5000 Watts (CW) short time
HI-P 4000	600 Watts (CW) continuous
	1800 Watts (CW) short time
Bandwidth @ SWR ≤ 2:	
	≥ 2600 kHz (230 channel)
Mounting:	
FIGHTER P-5000	hole Ø 12.5 mm, 0.5 in
FIGHTER P-5000 3/8	3/8" x 24 thread
FIGHTER P-5000 PL	UHF-male (PL 259)
FIGHTER HI-P 4000	UHF-male (PL 259)
Cable lenght / Type:	
FIGHTER P-5000	4 m, 13ft / RG 58
Other models	not supplied
Shaft version:	shaft 200mm, 8"



FIGHTER P-5000 3/8 w/o shaft

CONNECTION
3/8 x 24 THREADS



FIGHTER P-5000 3/8 w/shaft

200mm, 8"
STAINLESS
STEEL SHAFT

WITH CHROMED
BRASS FIXING NUT



P-5000 MATCHING COIL

Low loss dielectric support. Air wound big section copper wire Ø 2.5mm AWG 10



FIGHTER P-5000 & P-5000 PL

Black Chromed Joint



HI-POWER MATCHING COIL

Low loss dielectric support. Big section copper wire Ø 1.8mm AWG 13



FIGHTER HI-POWER 4000 PL

LIMITED EDITION